

Thank you for purchasing a Shakespeare antenna product. Customer comments are welcome. Before installing, please study the diagram and check parts supplied against those listed.

**IMPORTANT! Please read all instructions before installing.**

The Style 476 is a one-section, phased 1/2-wave collinear array, commercial VHF marine antenna of 21' (6.4 m) length.

**Installation Instructions**

Choose a mounting location that is as high as feasible, as free as possible from obstructions, and as far as possible from other antennas and strong sources of RF.

1. Mount the antenna.

For mast mounting, use the antenna's 2 3/4" x 26" aluminum sleeve, and strap it directly to the mast with suitable hardware (not supplied), or use a Shakespeare Style 483 Clamp Set (sold separately).

For bulkhead mounting, use Shakespeare Style 484 Wall Mounting Brackets (sold separately).


2. Connect the antenna to your transceiver using suitable coax cable (sold separately).

**IMPORTANT:** Do not mount or store this antenna in an inverted or horizontal position. Always position the antenna so moisture absorption or condensation can drain out between the aluminum sleeve and the coaxial connector.

This antenna requires no external or internal ground system, and works equally well on fiberglass, wood, or metal boats.

**Tech Tip:** This antenna will read DC short between the central conductor and the outer shell of the coaxial connector. Ground radials are not required.

Supplied Parts
1 Antenna assembly



35-90-1099-00

**Shakespeare Electronic Products Group**

U.S. Operations: 6111 Shakespeare Rd. · Columbia, SC 29223 · 803-227-1590 · Fax: 803-419-3099 · www.shakespeare-marine.com  
 U.K. Operations: Enterprise Way, Fleetwood, Lancashire, FY7 8RY, England · +44 (0) 1253 858787 · Fax: +44 (0) 1253-859595 · www.vtronix-antennas.com